### Electro-Voice®



## RMR2

# Rack Mount for the R2 Diversity Wireless Receiver

- Mounts a single R2 diversity receiver in one rack space
- Heavy-duty steel construction for durability
- Two screws hold the receiver firmly to the rack tray

#### **SPECIFICATIONS**

Materials:

Black enamel-painted steel, .06 in. thick **Included Hardware:** 

Two #4-40 x 3/8 self-tapping flathead screws, four #10-32 x 1/2 rack screws, four #10 dress washers

Dimensions,

Heiaht:

43.9 cm (1.73 in.)

Width:

482.6 cm (19 in.)

Depth:

127 cm (5.0 in.)

**Net Weight:** 

.82 kg (29 oz)

Shipping Weight:

1.03 kg (36.5 oz)

#### DESCRIPTION

The RMR2 is a single-rack-space kit for mounting the Electro-Voice R2 diversity receiver in a standard 19-inch rack. The kit consists of a one-rack-space tray with a cut-out for the face and antennae of the receiver, two screws to attach the receiver to the tray, and four rack screws with washers.

#### **MOUNTING THE R2 RECEIVER**

First, remove the four adhesive-mounted feet from the bottom of the R2 receiver by pulling sideways and up. Place the receiver in the tray with its front (display and antennae side) against and centered with the rectangular cut-out in front of the rack tray. Holding it in place, turn the

receiver and rack tray upside down and line up the two holes in the bottom of the rack tray with the two holes in the bottom of the receiver. Using the smaller screws, carefully screw the receiver to the rack tray until it is firmly attached. Use the included rack screws and washers to mount the unit into a rack.

#### UNIFORM LIMITED WARRANTY

Electro-Voice products are guaranteed against malfunction due to defects in materials or workmanship for a specified period, as noted in the individual product-line statement(s) below, or in the individual product data sheet or owner's manual, beginning with the date of original purchase. If such malfunction occurs during the specified period, the product will be repaired or replaced (at our option) without charge. The product will be returned to the customer prepaid. Exclusions and Limitations: The Limited Warranty does not apply to: (a) exterior finish or appearance: (b) certain specific items described in the individual product-line statement(s) below, or in the individual product data sheet or owner's manual; (c) malfunction resulting from use or operation of the product other than as specified in the product data sheet or owner's manual; (d) malfunction resulting from misuse or abuse of the product; or (e) malfunction occurring at any time after repairs have been made to the product by anyone other than Electro-Voice or any of its authorized service representatives. Obtaining Warranty

Service: To obtain warranty service, a customer must deliver the product, prepaid, to Electro-Voice or any of its authorized service representatives together with proof of purchase of the product in the form of a bill of sale or receipted invoice. A list of authorized service representatives is available from Electro-Voice at 600 Cecil Street, Buchanan, MI 49107 (616/ 695-6831 or 800/234-6831). Incidental and Consequential Damages Excluded: Product repair or replacement and return to the customer are the only remedies provided to the customer. Electro-Voice shall not be liable for any incidental or consequential damages including, without limitation, injury to persons or property or loss of use. Some states do not allow the exclusion or limitation of incidental or consequential damages so the above limitation or exclusion may not apply to you. Other Rights: This warranty gives you specific legal rights, and you may also have other rights which vary from state to state.

Electro-Voice Accessories are guaranteed against malfunction due to defects in materials or workmanship for a period of one (1) year from the date of original purchase. Additional details are included in the Uniform Limited Warranty statement.

Service and repair address for this product: Electro-Voice, Inc., 600 Cecil Street, Buchanan, Michigan 49107 (616/695-6831 or 800/234-6831).

Specifications subject to change without notice.

#### **RMR2 SPECIFICATION GRAPHICS**

FIGURE 1 — Dimensions

